



## JA-158J Wall button

It enables you to remotely trigger a panic alarm, control other appliances, can be used as a doorbell or to control the alarm system. Thanks to bi-directional communication the device both visually and acoustically signals confirmation of a successful action.

- 2W communication
- Tamper
- Acoustic indication
- Optical indication

### TECHNICAL SPECIFICATION

<b>Power</b>	2x Lithium Battery type CR 2032 (3.0 V/0.2 Ah)
<b>Typical battery lifetime</b>	approx. 5 years
<b>Maximum power consumption</b>	40 mA
<b>Compatibility</b>	control panels JA-103K, JA-107K
<b>Communication frequency</b>	868.1 MHz, Jablotron protocol
<b>Maximum radio-frequency output (ERP)</b>	8 mW
<b>Communication range</b>	approx. 300 m
<b>Classification</b>	Security grade 2 / environmental class II, (EN 50131-1)
<b>Environment</b>	Indoor general
<b>Ingress Protection Code</b>	IP 22
<b>Operational temperature range.</b>	-10 °C to +40 °C
<b>Dimensions</b>	80 x 80 x 20 mm
<b>weight (w/o batteries)</b>	58 g



### OTHER FUNCTIONALITIES

- ✓ INDEPENDENT BUTTONS
- ✓ DELAYED ACTIVATION